Molded Case Circuit Breakers

QJ 225A Frame

Continuous Current Rating @ 40°C	2-Pole 240V AC Catalog Number	3-Pole 240V AC Catalog Number
Type QJ2②		
60	**QJ22B060■**	**QJ23B060**
70	**QJ22B070■**	**QJ23B070**
80	**QJ22B080■**	**QJ23B080■**
90	**QJ22B090■**	**QJ23B090■**
100	**QJ22B100**	**QJ23B100**
110	**QJ22B110■**	**QJ23B110**
125	**QJ22B125**	**QJ23B125**
150	**QJ22B150**	**QJ23B150**
175	**QJ22B175**	**QJ23B175**
200	**QJ22B200**	**QJ23B200**
225	**QJ22B225**	**QJ23B225**
Type QJH2②		
60	**QJH22B060■**	**QJH23B060■**
70	**QJH22B070■**	**QJH23B070■**
80	**QJH22B080■**	**QJH23B080■**
90	**QJH22B090■**	**QJH23B090■**
100	**QJH22B100■**	**QJH23B100**
110	**QJH22B110■**	**QJH23B110**
125	**QJH22B125**	**QJH23B125**
150	**QJH22B150**	**QJH23B150**
175	**QJH22B175■**	**QJH23B175**
200	**QJH22B200**	**QJH23B200**
225	**QJH22B225**	**QJH23B225**
Type QJ2H②		
60	**QJ22B060H■**	**QJ23B060H■**
70	**QJ22B070H■**	**QJ23B070H■**
80	**QJ22B080H■**	**QJ23B080H■**
90	**QJ22B090H■**	**QJ23B090H■**
100	**QJ22B100H■**	**QJ23B100H**
110	**QJ22B110H■**	**QJ23B110H■**
125	**QJ22B125H**	**QJ23B125H**
150	**QJ22B150H**	**QJ23B150H**
175	**QJ22B175H■**	**QJ23B175H**
200	**QJ22B200H**	**QJ23B200H**
225	**QJ22B225H**	**QJ23B225H**
Type HQJ2②		
100	—	**HQJ23B100▲**
110	—	**HQJ23B110▲**
125	—	**HQJ23B125▲**
150	—	**HQJ23B150▲**
175	—	**HQJ23B175▲**
200	—	**HQJ23B200▲**
225	—	**HQJ23B225▲**

Ordering Information

Load side TA1Q300 lugs are mounted and included when circuit breaker is ordered. For line and load lugs (TA1Q300) installed at no additional charge, add suffix "L" to catalog number.

50°C Calibration - See page 7-91.
400HZ. - See page 7-91.

Shipping Weights

QJ2, QJH2, QJ2H, HQJ2		
Number of Poles	**Number per Carton**	**Shipping Weight (lbs.)**
2	10	30
3	10	41

Lugs For 75°C Wire①

Catalog Number	Lug Body	Lug Wire Range
TA1Q300	Al	(1) #6—300 kcmil Cu (1) #4—300 kcmil Al
TC1Q250	Cu	(1) #6—250 kcmil Cu

Enclosures (Neutral Included)

Type	Catalog Number
1	**EB3225**(S)(F)
3R (2-pole)	**WB2225**
3R (3-pole)	**WB3225**

UL 489 Interrupting Ratings

Breaker Type	RMS Symmetrical Amperes (kA) Volts AC (50/60 Hz)	
	240	208Y/120
QJ2	10	—
QJH2	22	—
QJ2H	42	—
HQJ2	65	100



4.5″ 3-pole

QJ2

Internal Accessories (Factory installed only) (3-pole only)③
Add suffix to catalog number.

Control Voltage		Shunt Trip	Auxiliary Switches		Shunt Trip and 1A and 1B Auxiliary Switch
			1A and 1B	2A and 2B	
AC	DC	Suffix	Suffix	Suffix	Suffix
120/240		**00S01■**	**A01■**	**A02■**	**01S01■**
	24	**00S07■**	**A01■**	**A02■**	**01S07■**
	48	**00S09■**	**A01■**	**A02■**	**01S09■**

■ Built to order. Allow 2–3 weeks for delivery.

▲ Built to order. Allow 6–8 weeks for delivery.

① See **Note: A** page 7-81.
Note: QJ breakers are UL Listed for reverse feed applications.

② HACR rated.
③ Internal accessories are not available on 2-pole QJ breakers.

Enclosures Section 6
For external accessories, please refer to pages 7-95 to 7-100