Breaker Type	Ampere Rating	Catalog Number	Catalog Number	UL Interrupting Ratings (kA)
QN 2-Pole 120/240V AC	150	**QN2150**	**QN2150R**②	10
	175	**QN2175**■	**QN2175R**②■	10
	200	**QN2200**	**QN2200R**②	10
QNH 2-Pole 120/240V AC	150	**QN2150H**	**QN2150RH**②	22
	175	**QN2175H**■	**QN2175RH**②■	22
	200	**QN2200H**	**QN2200RH**②	22
HQN 2-Pole 120/240V AC	150	**HQN2150**	**HQN2150R**②	65
	175	**HQN2175**■	—	65
	200	**HQN2200**	**HQN2200R**②	65

Requires 4 panel spaces, 2 adjacent and 2 opposite. **SHIPPING:** 1 per carton (Wt. 3 lbs.)



QNR⑤ **QN**⑤

Main Breaker Kits

For use in Ultimate Load Centers④			For use in EQIII Load Centers			
UL Type	Ampere Rating	Catalog Number	UL Type	Ampere Rating	Catalog Number	UL Interrupting Ratings (kA)
EQ8681	100	**MBK100A**	EQ9675	100	**MBK100**	22
EQ8682	125	**MBK125A**	EQ9677	125	**MBK125**	22
EQ8693	150	**MBK150A**	EQ9683	150	**MBK150**	22
—	—	—	EQ9684	175	**MBK175**■	22
EQ8695	200	**MBK200A**	EQ9685	200	**MBK200**	22
EQ8696	225	**MBK225A**	EQ9686	225	**MBK225**	22



EQ9675

Breaker Type	Ampere Rating	Catalog Number	UL Interrupting Ratings (kA)
QPJ③ 3-Pole 240V AC	125	**QPJ3125**	10
	150	**QPJ3150**	10
	200	**QPJ3200**	10

Requires 6 spaces due to cross over design. Fits only EQIII 125-400A 3-phase load centers

SHIPPING: 5 per carton (Wt. 17 lbs.)



MBK (100,125)A **MBK** (150,200,225)A

Breaker Type	Ampere Rating	Catalog Number	UL Interrupting Breaker Ratings (kA) Volts AC 120/240
QPP 2-Pole 120/240V AC	125	**Q2125B**	10
	150	**Q2150B**	10
	175	**Q2175B**■	10
	200	**Q2200B**	10
	225	**Q2225B**	10
QPPH 2-Pole 120/240V AC	125	**Q2125BH**	22
	150	**Q2150BH**	22
	175	**Q2175BH**■	22
	200	**Q2200BH**	22
	225	**Q2225BH**■	22
HQPH 2-Pole, 120/240V AC	100	**HQ2100H**	100
	125	**HQ2125H**	100
HQPP 2-Pole 120/240V AC	125	Obsolete	
	150		
	175		
	200		
	225		
HQPPH 2-Pole 120/240V AC	100	Obsolete	
	125		
	150		
	175		
	200		
	225		



QPJ



2-Pole **QPP**

For inches / millimeters conversion, see Application Data section.
■ Built to order. Allow 2–3 weeks for delivery.

① All circuit breakers on this page are common trip.
② Reverse handle.
③ CSA Listed.
④ MBK100A for use in 100 and 125A load centers.
MBK125A for use in 125A load centers.
MBK150A for use in 150, 200 and 225A load centers.
MBK200A for use in 200 and 225A load centers.
MBK225A for use in 225A load centers.
MBK175A for use in 200 and 225A load centers.

⑤ QNR required for horizontal applications or vertical applications where the lugs are facing up. The QN breaker is required for vertical applications where the lugs are facing down as shown.